



# NT-I80 IR Camera

## ≈Specifications≈

BLC	Auto
Power Requirements	12V DC
Power Consumption	IR on-400mA, IR off 80mA
Sensitivity	0.2Lux, 0 Lux at /IR on
Gamma Correction	0.45
IR Distance	80 meters (subject to IR conditions)
DNR	Built-in digital noise reduction
Auto Gain Control	Auto +18dB Max
Signal to Noise	More than 52dB
Scanning System	NTSC - 525 lines 2:1 Interface PAL - 625 lines 2:1 Interface
Horizontal Resolution	520 TV Lines
Electronic Shutter	NTSC - 1/60- 1/100,000 sec PAL - 1/50 - 1/100,000 sec

## ≈Features≈

- ◆ Built-in Digital Noise Reduction color CCD
- ◆ Built-in Hidden - cable Bracket
- ◆ IR Distance: 80 Meters
- ◆ Long Life IR LED (up to 10,000 hours)
- ◆ Smart IR on/off control
- ◆ IP66 Weatherproof housing

### Hidden-Cable Bracket



Midland Telecom Inc.

3239 West 2nd Street  
P.O. Box 2151  
Grand Island, NE 68802

Phone:(308) 381-4000  
Toll Free: (888) 669-1931  
Fax: (308) 381-2801