

AX Series

Integrated Audio & Video Security

Features

- Up to 8 master stations and 120 remote stations
- Clearly identify visitors from behind locked entrances
- Communicate between offices, entrances, and classrooms, etc.
- Enhances existing security systems
- Wide variety of programmable features
- Unlock doors at the touch of a button (remote door release)
- Video door stations with built-in access card readers allow for keyless entry
- Make general or emergency paging announcements with voice notification
- Fully scalable up to 120 door stations for entrances or classrooms, etc
- Transfer calls from any door or sub station to a telephone or cell phone.



Master Stations quickly identify visitors and can communicate with all other door, sub, and master stations.



Interior and exterior door stations allow visitors and vendors to request access into a particular room or building.



Specifications

Power Source	24V DC - Use two PS-2420UL (110V AC) per system
Door Station Calling	Tremolo call tone programmable from 10-600 seconds, or infinite. LCD monitor remains on for duration of call tone up to 10 minutes max.
Master Station Calling	Select station to call, pretone sounds, then speak hands-free or push-to-talk
Video Monitor	3.5" direct view TFT color LCD
Door Release	N/O or N/C, programmable per station 24V AC/DC (500mA max.)
Wiring	CAT-5e UTP-4 homerun from each station to CEU
Distance	Door station to CEU: 980' Master station to CEU: 980'
CO Tel Adaptor	Viking Model K-1900-5 Programmable Dialer